

SELF-TIMED SNEAK CURRENT CANCELLATION**BACKGROUND**1. Field

5 This disclosure relates to passive electronic devices, more particularly to passive electronic devices that are subjected to applied voltages.

2. Background

Passive electronic devices generally do not generate signals based upon their own internal circuits. Typically, passive devices must be addressed or requested to provide
10 some sort of signal. One example of a passive device is a memory. Generally, memories do not provide the data stored in them until some other device, such as a processor, requests the data. Similarly, the memory receives data to store, rather than generating data to store.

In some types of passive devices, including memories, have elements being held at
15 a potential, even though those elements may not be undergoing active addressing. Returning to the memory example, for example, a memory cell may be held at a particular potential in order to allow the cell to retain the data stored there. This potential is typically less than that required to address a cell for either reading or writing.

However, application of the voltage may cause the cell to 'leak' charge over a
20 period of time, resulting in a low level of current. While the current created by any one element does not cause problems, when multiplied by the number of elements in the device, the current could become one. The cumulative charge over time becomes a significant current, referred to here as 'sneak' current, and results in a high level of noise in the signal.

25 It would be desirable for a method and apparatus that could cancel the sneak current, reducing the noise in the system utilizing the passive electronic devices.

BRIEF DESCRIPTION OF THE DRAWINGS

The invention may be best understood by reading the disclosure with reference to the drawings, wherein:

Figure 1 shows an embodiment of a passive electronic device.

5 Figure 2 shows an embodiment of an array of memory cells, in accordance with the invention.

Figure 3 shows an embodiment of a voltage versus polarization hysteresis curve, in accordance with the invention.

Figure 4 shows an embodiment of a read cycle, in accordance with the invention.

10 Figure 5 shows an embodiment of a sense and interpretation circuit, in accordance with the invention.

Figure 6 shows an embodiment of a self-timing module, in accordance with the invention.

Figure 7 shows an embodiment of a timing diagram for self-timed sneak current
15 cancellation, in accordance with the invention.

DETAILED DESCRIPTION OF THE EMBODIMENTS

Figure 1 shows one example of a cell in a ferroelectric memory array. The cell 10 has an electrode layer 22, a ferroelectric material layer 16 and a second electrode layer 20. This cell may be manufactured by depositing and patterning a layer of metal, depositing a
20 polymer and then depositing and patterning another layer of metal. There are no transistors or other semiconductor elements in each cell, simplifying both the structure and the manufacturing process of these types of memories.

The electrode layers 20 and 22 are typically organized such that one forms a series of lines oriented in a first direction and the other forms a series of lines in a direction at a
25 right angle to the first direction. Although these lines are separated by the ferroelectric material, they do cross over forming the grid of memory cells. The region of ferroelectric

material 16 sandwiched between the two lines at the crossover point shown in Figure 1 is the portion of the cell that holds the data value as will be discussed in more detail further.

Figure 2 shows a portion of a memory array formed of such cells. The electrode line 20 from Figure 1 is defined as a word line and the electrode line 22 as the bit line.

5 The cell 10 is at the cross over point of these two lines and in this example is the active cell. The active cell for the purposes here is that cell which is being addressed in a memory operation, either a memory read or a memory write. Correspondingly, the word line 20 is defined as the active word line (AWL) and word line 22 is defined as the active bit line (ABL). The word and bit lines surrounding the active cell are referred to as
10 passive word lines (PWL) and passive bit lines (PBL).

The data value in the cell is either a one '1' or a zero '0'. The value of the cell is determined by the polarization of the material versus the voltage being applied. Referring now to Figure 3, a polarization versus voltage hysteresis curve demonstrates the nature of the memory cell and how it stores data values of ones or zeros. Control of the voltages
15 applied to the active word line and active bit line may cause the material to experience a polarization shift. The differential voltage seen at the cell is referred to as the word line to bit line voltage, and is shown in the curve of Figure 3 as the horizontal axis. The vertical axis is the polarization of the material. The origin of the axes corresponds to zero voltage and zero polarization. Figure 3 shows a typical polarization versus voltage curve.

20 When a negative voltage $-V_s$ is applied to the word line 20 relative to bit line 22, the polarization versus voltage profile follows the left path 40. This occurs as the polarization of the ferroelectric material switches from positive to negative polarity. Changes in polarization take time and eventually the polarization settles at the polarization level corresponding to the negative saturation voltage $-V_s$, as shown at the
25 bottom of the leftmost path at 42. When the magnitude of the applied voltage is reduced,

shown here as being reduced to zero along path 35, the material retains a remnant polarity shown as a data value one on the vertical axis at 36.

Similarly, when a positive saturation voltage V_s is applied to word line 20 relative to bit line 22, the polarization versus voltage profile follows the right side path 38, settling at the polarization level corresponding to the positive saturation voltage, as shown at the top of the rightmost path at 44. When the applied voltage is reduced, shown here as being reduced to zero along path 34, the remnant polarity shown as a data value zero on the vertical axis shown at 32.

In order to determine the current state of polarity of a cell, the saturation voltage V_s is applied to the ferroelectric cell. This means that the word line to bit line voltage differential is V_s . This application causes a polarization shift. For the data value zero, where the cell has positive polarity at zero voltage, application of the saturation voltage produces little to no charge out. Sense amplifiers assigned to that cell detect some charge release, but not nearly as much as from cells having negative polarity at zero voltage. This lack of charge release is then manipulated to produce a data value of 'zero' for that memory cell in the read operation. However, application of the saturation voltage to the cells having negative polarity at zero voltage does cause a polarity reversal and an associated charge release. This charge release is sensed and manipulated to produce a data value of 'one' for that memory cell in the read operation.

One characteristic of this type of memory is that cells coupled to the active bit line experience a voltage potential of $V_s/3$. Referring back to Figure 2, these are the cells between the passive word line (PWL) and the active bit line (ABL). Cells release a residual amount of charge and form a "sneak current" to the active bit line. In one embodiment of the present invention, a residual charge release in the hundredths of femtocoulombs per memory cell, is expected for propagation to the active bit line. Assuming, for example, that thousands of ferroelectric cells are tied to the active bit line

and a worst case condition of each cell having a one state condition, then the combined “charge” propagated to the active bit line could be in the tenths of femtocoulombs per bitline. This charge may lead to a false reading of the memory cell, as it essentially acts as ‘noise’ on the line.

5 A timing diagram for a read cycle is shown in Figure 4. As can be seen, the four different types of data lines are shown on the timing diagram, being passive word lines (PWL), passive bit lines (PBL), active word lines (AWL) and active bit lines (ABL). In addition, a waveform for a sneak current and the cell charge are also shown. As can be seen, the word and bit lines are held at a potential of $V_s/3$, prior to the beginning of the cycle.

10 At time S_0 , as shown in the timing diagram of Figure 4, the word lines and bit lines receive quiescent level voltages of $V_s/3$. A sneak current 58 is then drawn from the active bit line discharging the active bit line to zero volts, as represented by waveforms 52, 56 at snapshot time S_1 in Figure 4. The sneak current is produced by the PWL to ABL voltage differential of $V_s/3$. In this embodiment a bit line settling duration of $S_3 - S_1$ is provided before starting a first integration interval.

15 After the time for the sneak current to reach a substantially linear region of its settling curve, the integration sense amplifier is enabled at snapshot time S_3 , to begin a first integration time window. Next, the active word line is charged to a read level voltage equal to the saturation level V_s as represented by waveform 54 at time S_2 . The integrating sense amplifier provides an integration to integrate charge released from the active ferroelectric cell. Upon conclusion S_4 of the first integration window, a first integration value is obtained from the integration sense amplifier.

20 After obtaining the first integration value, the integration sense amplifier is disabled and the active word line returned to its quiescent voltage level of $V_s/3$, as represented by waveform 54 at snapshot time S_5 . Another duration is allowed to lapse,

during which the active ferroelectric cell is allowed to establish a zero state remnant polarization condition, and then the integrating sense amplifier is again enabled to start the second integration window at time S_9 , and the active word line is driven to a read level voltage equal to the saturation level voltage V_s , see waveform 54 at time S_8 . Over this
5 second integration duration, residual charge released from the ferroelectric cell, as associated with any residual polarization alignments, is integrated by the integration sense amplifier.

At the conclusion of the second integration time window, at time S_{10} , a second integrated value is obtained from the sense amplifier, and the first and second integration
10 values are compared in order to determine the initial state of the ferroelectric cell. Following the second integration time window, the active word line is returned to its quiescent level voltage $V_s/3$ as represented by waveform 54 at time S_{11} , and the active and passive bit lines returned to their quiescent level voltages of $V_s/3$ as represented by waveforms 56, and 52.

15 In order to eliminate the problems associated with the sneak current, different approaches may prove useful. One such approach is shown in block diagram form in Figure 5. In this embodiment the circuit shown in Figure 5 is used to sense and interpret the polarization charge release from an addressed pixel during a read cycle. As part of the read cycle, the circuit provides for mitigation of the effects of the sneak current.

20 As can be seen in Figure 5, the sense and interpretation circuit has four functional blocks in this embodiment. The integrator, INT_LV, 66 senses the charge release on the addressed bit line, BL_DAT. The integrator 66 produces an output voltage proportional to the charge. A comparator, COMP, 68 with a threshold voltage adjustable through THRES_ADJ interprets this voltage as a "1" or a "0," which is presented on DOUT. The
25 integration mode signal INTG_MODE controls the timing of the integrators to handle sneak current using the SELFTIME module 64. The SELFTIME module 64 has an input

of VREF, which is produced by the SNEAKREF compensation module 62. This will be discussed in more detail later.

A more detailed view of an embodiment of the SELFTIME module 64 is shown in Figure 6. The SELFTIME module has essentially two different parts. A digital part, shown as the controller 70, decodes the integration mode signal INTG_MODE and generates the corresponding control signals. An analog part determines when to stop the integration of the VREF signal used in detecting the polarization state of the addressed cell. The analog part has a threshold voltage generator 72, an amplifier or pre-amplifier 76 and a comparator 74.

The voltage generator is used to set the threshold voltage to be compared with VREF. The level of the threshold voltage will typically be determined externally using the signal SELFTIME_ADJ. However, other means of determining the threshold voltage are also possible. The voltage generator 72 then generates a voltage at this level and passes that voltage to the comparator 74. The comparator will compare the reference voltage VREF to the threshold voltage and determine when VREF has reached the predetermined threshold voltage.

VREF is the bias voltage used in the integrators, typically adjusted for sneak currents. The sneak currents are monitored on a reference bit line BL_REF and the voltage on VREF is adjusted accordingly. This signal is amplified by the amplifier 76 prior to entering the comparator 74. To sense data on BL_DATA correctly, typically zero data is written into the reference cells.

The circuit of Figure 6 is just one embodiment of a self-timing circuit and may have several different types of integration modes. For purposes of discussion here, the integration mode discussed with reference to Figures 6 and 7 will be referred to as self-timing sneak current cancellation and will be designated as integration mode 00. Other integration modes are possible, but are outside the scope of this disclosure.

Referring now to Figure 7, the interaction between the self-timed sneak current cancellation and a read cycle may be better understood. Generally, a sample of the integrators is taken when VREF has reached the threshold voltage. In the dual read mode discussed with regard to Figure 4, the second sample is taken when VREF reaches a voltage level substantially equal to the threshold voltage, similar to the taking of the first sample. The second integration may take slightly longer than the first. A read signal, SENSE_READY_OUT, is generated each time a sample is taken. In addition, there is a programmable timeout function that may cause the sample to be taken before the threshold is reached. The sample taken is of the output voltage of the integrators.

In Figure 7, the various signals in the timing diagram are as follows. Some of these are not shown in Figure 6, as they are control signals to the various components of the circuit and are somewhat self-explanatory.

Signal Name	Description
PWRON	Power up signal
SENSE RESET	Reset signal for the integrators
SA_CONNECT	Connect the integrators to the bit lines and the SNEAKREF module to the reference bit line
BL_PRECH	Precharge signal for the reference bit line
VBL_ACT	Voltage on the active bit line
Active data BL	Bit line being addressed
Active ref BL	Active reference bit line
Active WL	Word line being addressed
SENSE STOP	Timeout signal
SENSE READY	Signal indicating a sample is to be taken from integrators
DOUT	Data out

The relevant points of time in the timing diagram are designated with a lower case letter.

At 'a' the sense amplifiers are powered up and the integrators enter their reset state. The active bit line and the reference bit line are precharged to the voltage on the VBL_ACT. At the end of 'b' the column strobe connects the data and reference bit lines to BL_DATA and BL_REF lines, respectively. At 'c' the precharge period ends and the BL_DATA and BL_REF lines are connected to the amplifiers through SA_CONNECT.

Integration starts as the integrators exit their reset state at 'd.' The addressed word line is then switched to V_s to allow the full switching potential to lie across the addressed cells of the memory array at 'e.' At 'f' the sneak charge on the reference bit line has reached the threshold, or the SENSE_STOP signal is triggered by a timeout.

- 5 SENSE_READY is set high and the comparator samples the output of the integrator. This ends the first integration.

- At points 'g', and 'h', the process resets to allow the second sensing period to commence. At 'g' the BL_DAT and BL_REF lines are disconnected from the amplifiers and the integrators are reset. The active word line is also switched back. At 'h'
- 10 VBL_ACT is switched to a dwelling voltage or left alone and BL_DAT and BL_REF follow.

- The second sensing period commences at 'i' when VBL_ACT returns to its inactive state, and BL_DAT and BL_REF follow. For purposes of this discussion, and as shown in Figure 4, the inactive state for VBL_ACT is assumed to be zero volts.
- 15 However, there may be a bias voltage applied, V_{BL} , to which VBL_ACT is precharged. The points 'k,' 'l,' and 'm' correspond to points 'd,' 'e,' and 'f.' The process cycles down at 'n' when BL_DAT and BL_REF are disconnected from the amplifiers and the addressed word line is switched back. Finally, at 'o' the sense amplifiers power down, the column strobe turns off and the bit lines return to the quiescent voltage.

- 20 In this manner the sneak current is first collected by self-timing the integration periods to allow the VREF to reach a predetermined level. Since VREF includes the sneak current, the possibility of a false reading is mitigated. The results of the two sensing operations are subtracted to ensure that all influences of the sneak current are eliminated.

- 25 Thus, although there has been described to this point a particular embodiment for a method and apparatus for self-timed sneak current cancellation, it is not intended that

such specific references be considered as limitations upon the scope of this invention except in-so-far as set forth in the following claims.

100 101 102 103 104 105 106 107 108 109 110 111 112 113 114 115 116 117 118 119 120 121 122 123 124 125 126 127 128 129 130 131 132 133 134 135 136 137 138 139 140 141 142 143 144 145 146 147 148 149 150 151 152 153 154 155 156 157 158 159 160 161 162 163 164 165 166 167 168 169 170 171 172 173 174 175 176 177 178 179 180 181 182 183 184 185 186 187 188 189 190 191 192 193 194 195 196 197 198 199 200 201 202 203 204 205 206 207 208 209 210 211 212 213 214 215 216 217 218 219 220 221 222 223 224 225 226 227 228 229 230 231 232 233 234 235 236 237 238 239 240 241 242 243 244 245 246 247 248 249 250 251 252 253 254 255 256 257 258 259 260 261 262 263 264 265 266 267 268 269 270 271 272 273 274 275 276 277 278 279 280 281 282 283 284 285 286 287 288 289 290 291 292 293 294 295 296 297 298 299 300 301 302 303 304 305 306 307 308 309 310 311 312 313 314 315 316 317 318 319 320 321 322 323 324 325 326 327 328 329 330 331 332 333 334 335 336 337 338 339 340 341 342 343 344 345 346 347 348 349 350 351 352 353 354 355 356 357 358 359 360 361 362 363 364 365 366 367 368 369 370 371 372 373 374 375 376 377 378 379 380 381 382 383 384 385 386 387 388 389 390 391 392 393 394 395 396 397 398 399 400 401 402 403 404 405 406 407 408 409 410 411 412 413 414 415 416 417 418 419 420 421 422 423 424 425 426 427 428 429 430 431 432 433 434 435 436 437 438 439 440 441 442 443 444 445 446 447 448 449 450 451 452 453 454 455 456 457 458 459 460 461 462 463 464 465 466 467 468 469 470 471 472 473 474 475 476 477 478 479 480 481 482 483 484 485 486 487 488 489 490 491 492 493 494 495 496 497 498 499 500 501 502 503 504 505 506 507 508 509 510 511 512 513 514 515 516 517 518 519 520 521 522 523 524 525 526 527 528 529 530 531 532 533 534 535 536 537 538 539 540 541 542 543 544 545 546 547 548 549 550 551 552 553 554 555 556 557 558 559 560 561 562 563 564 565 566 567 568 569 570 571 572 573 574 575 576 577 578 579 580 581 582 583 584 585 586 587 588 589 590 591 592 593 594 595 596 597 598 599 600 601 602 603 604 605 606 607 608 609 610 611 612 613 614 615 616 617 618 619 620 621 622 623 624 625 626 627 628 629 630 631 632 633 634 635 636 637 638 639 640 641 642 643 644 645 646 647 648 649 650 651 652 653 654 655 656 657 658 659 660 661 662 663 664 665 666 667 668 669 670 671 672 673 674 675 676 677 678 679 680 681 682 683 684 685 686 687 688 689 690 691 692 693 694 695 696 697 698 699 700 701 702 703 704 705 706 707 708 709 710 711 712 713 714 715 716 717 718 719 720 721 722 723 724 725 726 727 728 729 730 731 732 733 734 735 736 737 738 739 740 741 742 743 744 745 746 747 748 749 750 751 752 753 754 755 756 757 758 759 760 761 762 763 764 765 766 767 768 769 770 771 772 773 774 775 776 777 778 779 780 781 782 783 784 785 786 787 788 789 790 791 792 793 794 795 796 797 798 799 800 801 802 803 804 805 806 807 808 809 810 811 812 813 814 815 816 817 818 819 820 821 822 823 824 825 826 827 828 829 830 831 832 833 834 835 836 837 838 839 840 841 842 843 844 845 846 847 848 849 850 851 852 853 854 855 856 857 858 859 860 861 862 863 864 865 866 867 868 869 870 871 872 873 874 875 876 877 878 879 880 881 882 883 884 885 886 887 888 889 890 891 892 893 894 895 896 897 898 899 900 901 902 903 904 905 906 907 908 909 910 911 912 913 914 915 916 917 918 919 920 921 922 923 924 925 926 927 928 929 930 931 932 933 934 935 936 937 938 939 940 941 942 943 944 945 946 947 948 949 950 951 952 953 954 955 956 957 958 959 960 961 962 963 964 965 966 967 968 969 970 971 972 973 974 975 976 977 978 979 980 981 982 983 984 985 986 987 988 989 990 991 992 993 994 995 996 997 998 999 1000